



Programming / Commissioning Your System - The Charge Controller


Charge Control Settings for LifeBlue Lithium Batteries:

1. Download the "VictronConnect" App to your phone.
2. Open the App.
3. You'll see a selection for your SmartSolar MPPT Charger, select it.
4. Type **000000** to login for the first time.
NOTE: To change the PIN code, go back one step to the main screen. Click on the 3 buttons to the right of the controller image, and select "Reset PIN Code".
5. Click on the **gear** in the top right corner.
6. Click on "Battery".
7. Click on the settings and adjust them accordingly to match below:


- Battery voltage: 12V
- Max charge current: 50A (In this example)
- Charger enabled: ON
- Battery Preset: User defined
- Expert Mode: ON
- Absorption voltage: 14.50 V
- Float voltage: 13.70 V
- Equalization voltage: 14.50 V
- Re-bulk voltage offset: 0.10V
- Absorption Duration: Fixed (Must Enable Expert Mode within Victron Connect)
- Absorption Time: 00:20 (20 minutes)
- Tail Current: .5A per 100Ah of total capacity
- Auto Equalization: Disabled (Off)
- Temperature compensation: Disabled (Off)




Absorption Voltage	14.5v
Activate Expert Mode	Yes
Absorption Duration	Fixed
Absorption Time Limit	20 Minutes
Float Voltage	13.7v
Equalization Voltage	14.5v
Tail Current	.5 per 100Ah
Auto Equalization	No
Temperature Compensation	Off



Device List within VictronConnect



MPPT Charge Controller Screen



Battery Settings Screen